

CM0001x MAIN FIRMWARE RELEASE NOTES

Ishida Uni-10 Series – with Support for the Epson ColorWorks Printer

Procedure to Install Uni-10 Firmware

Refer to the *Uni-10 Setup Manual* for complete information.

1. Copy the scale firmware folder "Soft" onto an empty USB memory stick.
 - The "Soft" folder itself must not be zipped even if some files in the folder are.
 - The "Soft" folder should be the only data on the USB memory stick.
2. Power up the scale and press the green **ENTER** button at the Date/Time confirm screen.
3. Open the access panel on the left side of the scale and insert the USB memory stick into any of the four USB ports.
 - No other USB devices should be connected.
4. Press the **RETURN ARROW** key (upper right) to enter the Main menu.
5. Press the **LOGIN** key (lower left).
6. Enter **495344** and press the **PLU** key to access hidden menu steps.
7. Press the **ADJUST** menu button.
8. Select **DOWNLOAD**.
9. Press the firmware version to be installed. It will be highlighted in yellow.
10. Press **EXEC** to confirm the selection.
11. Press **EXEC** to begin the firmware download.
12. The screen will show the firmware download progress. The download will take several minutes to complete.
13. When the Re-Boot Check message 15029-0002 is displayed, the firmware download is complete. The scale will automatically reboot.
14. Press the green **ENTER** button at the Date/Time confirm screen.
15. Press the **RETURN ARROW** key (upper right) to enter the Main menu. Then press the **LOGIN** key (lower left).
16. Enter **495344** and press the **PLU** key to access hidden menu steps.
17. Press the **ADJUST** menu button, then select **MEMORY CLEAR**.
18. Press **CLEAR** to ensure there is no unintended data resulting from the new firmware.
19. Press **EXEC** to confirm the memory clear.
20. Press the **RETURN ARROW** key (upper right) after the result of **OK** is displayed.
21. From the **ADJUST** menu select **DOWNLOAD**.
22. Press the **SUB APP** tab.
23. Press the program to be installed. It will be highlighted in yellow. Select only one Sub App program at a time.
24. Press **EXEC** to confirm the selection. Press **EXEC** to begin the firmware download.
25. The screen will show the firmware download progress. The download will take several minutes to complete.
26. When the Re-Boot Check message 15029-0002 is displayed the firmware, download is complete. The scale will automatically reboot.
27. Press the green **ENTER** button at the Date/Time confirm screen.
28. Press the **RETURN ARROW** key (upper right) to enter the Main menu.
29. Press the **LOGIN** key (lower left).
30. Enter **495344** and press the **PLU** key to access hidden menu steps.
31. Repeat steps 21 ~ 27 to load the remaining Sub App programs.
32. Remove the USB memory stick.

CM0001x MAIN FIRMWARE RELEASE NOTES
Ishida Uni-10 Series – with Support for the Epson ColorWorks Printer

Table of Contents

Procedure to Install Uni-10 Firmware	1
Version CM0001G	3
Version CM0001F	4
Version CM0001E1	5
Version CM0001E	6
Version CM0001D	7
Version CM0001C12	8
Version CM0001C10	9
Version CM0001C6	9
Version CM0001C5	10
Version CM0001C	11
Version CM0001B	12
Version CM0001A	13
Version CM0001	14

CM0001x MAIN FIRMWARE RELEASE NOTES

Ishida Uni-10 Series – with Support for the Epson ColorWorks Printer

Version CM0001G

Release Date: October 2024

Use with SLP-5 **2.62** or later (required for compatibility)

Main: **CM0002G**
Scale Driver: J0994 (J0835)
OS:
 12.1 inch J1100-4
 10.1 inch J1100-2
BOOT: J1072C
FPGA App.: J1101
Scale: J0776L or later
Printer App: B0809B or later

NOTES:

- a) After downloading the Main program, download the Printer Sub App and FPGA Sub App programs one at a time as needed.
- b) After changing the color printer connection method or IP address the Uni-10 must be rebooted to activate the change [Setup menu → Machine No. → Outside Printer]



Caution

Memory initialization may be required when upgrading to this firmware version. Use SLP-5 Maintenance Utility and SLP-5 to backup the scale before upgrading from firmware **CM0001E1** or an earlier version. Due to significant changes in the memory structure, after firmware installation a standard memory clear will be necessary: **Master Data Clear** (Adjust menu → Memory Clear) & **System Data Init.** (Setup menu → File Save/Load → Scale Init. tab). [8.6.1921.6]

The following lists the main changes from the previous version (CM0001F1).

1. Modified the Auto Return justification options for variable text fields to eliminate short lines and broken words.
 - a. There are three options:
 - 04: AUTO RETURN - NO CR LEFT
 - 05: AUTO RETURN - NO CR CENTER UP
 - 06: AUTO RETURN - NO CR RIGHT
 - b. As of ScaleLink Pro 2.64 these three options are not included. These are the steps to add the justification options.
 - i. Open the *SLP-5 Setup Utility*.
 - ii. Select **Label Format**.
 - iii. Select "Uni-10".
 - iv. Select **Unit Properties Setup**.
 - v. Select **Justification**.
 - vi. Edit the "0004 Auto line wrap" description and save:
 - Name: *Auto Line Wrap – Top Left*
 - Value: 4
 - vii. Click New, add the following to options and save:
 - Name: *Auto Line Wrap – Top Center*
 - Value: 5
 - Name: *Auto Line Wrap - Top Right*
 - Value: 6
 - viii. Click OK, Close (X), Save and Close (X).

CM0001x MAIN FIRMWARE RELEASE NOTES

Ishida Uni-10 Series – with Support for the Epson ColorWorks Printer

- ix. Close the Setup Utility
2. Modified the PLU preset key to display four lines of description when auto-populated by Top Seller Update or preset programming at the scale. The lines are limited to the first 16 characters. There is no word wrap to the next line. Any characters on a line beyond 16 will be cut off. Set the key width and character size accordingly.
3. Fixed a bug where the scale would lock up if the PLU description contained a "%" symbol, the PLU description was displayed using function key 431: PLU Name, and the scale was configured for self-serve mode.

Version CM0001F

Release Date: August 2024

Use with SLP-5 **2.62** or later (required for compatibility)

Main: **CM0002F**
Scale Driver: J0994 (J0835)
OS:
 12.1 inch J1100-4
 10.1 inch J1100-2
BOOT: J1072C
FPGA App.: J1101
Scale: J0776L or later
Printer App: B0809B or later

NOTES:

- a) After downloading the Main program, download the Printer Sub App and FPGA Sub App programs one at a time as needed.
- b) After changing the color printer connection method or IP address the Uni-10 must be rebooted to activate the change [Setup menu → Machine No. → Outside Printer]



Caution

Memory initialization is required when upgrading to this firmware version. Use SLP-5 Maintenance Utility and SLP-5 to backup the scale before upgrading from firmware **CM0001E1** or an earlier version. Due to significant changes in the memory structure, after firmware installation a standard memory clear will be necessary: **Master Data Clear** (Adjust menu → Memory Clear) & **System Data Init.** (Setup menu → File Save/Load → Scale Init. tab). [8.6.1921.6]

The following lists the main changes from the previous version (CM0001E1).

1. Modified the confirmation when the calibration save button is pressed to be one long beep.
2. Fixed a bug where sending the preset keyboard to the scale from ScaleLink Pro 5 caused error 12 Invalid Data. This was due to improper handling of the keyboard width for some of the secondary pages that are wider than 999 dots.
3. Fixed a bug that caused the scale to lock up when PLUs send from ScaleLink Pro 5 with two lines of description were added to the accumulator via the ADD function.
4. Added the "WPA2 PSK TKIP" encryption option. (Setup menu → Machine No. → WiFi tab).
5. Fixed a bug where the online status icon was inaccurate. Note that the "Connection Check Method" must be set as "PING" in order to properly ping the designated PC IP Address. (Setup menu → Machine No. → PC Com tab).
6. Fixed a bug where the Unit Price printed as "0.00" for Fixed Price PLUs programmed with a fixed bakery weight.

CM0001x MAIN FIRMWARE RELEASE NOTES

Ishida Uni-10 Series – with Support for the Epson ColorWorks Printer

7. Added an option to Standby Mode to select the operator and customer display independently. The default is "YES" for both displays to dim in Standby Mode (Setup menu).
8. Fixed a bug where the Search screen displayed a font size in Japanese characters when using function key 521: Message Search.
9. Modified the label format Unit (field) Details to display the Print ID value in decimal format to match the Print ID list.
10. Fixed a bug where the label preview did not display the dates and prices correctly in Label Format (Setup menu).
11. Modified the PLU's Fixed Weight field to accept up to "30000" from SLP-5 when the Sales Mode is 3: Case Weight. The maximum remains "999" for fixed ounce weight when the Sales Mode is 1: Fixed Price.
Note: Do not send Case Weight values over "999" to other models – it will cause a comms error. Only the Uni-10 will accept the higher values for fixed weight.
12. Modified custom barcode fields to support QR Codes. This is in addition to "Custom Barcode(QR)" (Print ID 119).
 - a. CUSTOM BARCODE (Print ID 113)
 - b. CUSTOM BARCODE2 (Print ID 120)
13. Added support to display a QR Code in Self-Service mode for weight check prior to distribution packaging. This feature is only available in Self-Service mode.
 - a. Added preset function key 473: WEIGHT CHECK to the main Self-Service page (Program menu → Preset Key → 7: Self → Jump Group 1).
 - b. The function key calls label format 998.
 - c. Create a customer barcode with ID 236: WEIGHT (USA).
 - d. Add QR Code: "Custom Barcode(QR)" (Print ID 119) to format 998 and link it to the custom barcode.
 - e. With no PLU called, place weight on the scale and press the function key 473: WEIGHT CHECK to display label format 998 and the QR Code.
 - f. Press the Back button to return to the main screen.
14. Modified the PLU NAME preset function key to display a label preview when pressed if the scale is in Self-Service mode (preset key ID 431).
 - a. Label format 999 is used for the label preview.
 - b. If the Return button is not pressed within four seconds the scale returns to the main operation screen – clearing the PLU. If the PLU is a Weighed item and weight is on the platter the display will remain at the label preview.
 - c. If label format 999 contains a custom barcode the actual data is displayed in the barcode.
15. Added an option for clearing the PLU's label preview during Self-Service mode.
 - a. The setting AUTO PLU0 CALL AFTER DISP. LABEL has been added (Setup menu → Operation Settings → Self tab).
NO – The display will remain at the label preview indefinitely. (default)
YES – If the Return button is not pressed within four seconds the scale returns to the main operation screen – clearing the PLU. If the PLU is a Weighed item and weight is on the platter the display will remain at the label preview until four seconds after the weight is removed.

Version CM0001E1

Release Date: June 2024

Use with SLP-5 2.62 or later ([required](#) for compatibility)

CM0001x MAIN FIRMWARE RELEASE NOTES

Ishida Uni-10 Series – with Support for the Epson ColorWorks Printer

Main: **CM0002E1**
Scale Driver: J0994 (J0835)
OS:
 12.1 inch J1100-4
 10.1 inch J1100-2
BOOT: J1072C
FPGA App.: J1101
Scale: J0776L or later
Printer App: B0809B or later

NOTES:

- a) After downloading the Main program, download the Printer Sub App and FPGA Sub App programs one at a time as needed.
- b) After changing the color printer connection method or IP address the Uni-10 must be rebooted to activate the change [Setup menu → Machine No. → Outside Printer]



Caution

Memory initialization is required when upgrading to this firmware version. Use SLP-5 Maintenance Utility and SLP-5 to backup the scale before upgrading from firmware **CM0001E** or an earlier version. Due to significant changes in the memory structure, after firmware installation a standard memory clear will be necessary: **Master Data Clear** (Adjust menu → Memory Clear) & **System Data Init.** (Setup menu → File Save/Load → Scale Init. tab). [8.6.1921.6]

The following lists the main changes from the previous version (CM0001E).

1. Modified the receipt barcode setup to remove the "Custom" option. If selected the Uni-10 would lock up when the accumulated label was printed.
2. Changed the time to 12-hour format at the following:
 - Operation mode - top bar.
 - Preset function key 505: MASTER RECEIVE TIME.
 - Default label formats 1, 10, 12, 78, 901, 906, 907, 911, and 916-919.

Version CM0001E

Release Date: May 2024

Use with SLP-5 **2.62** or later (required for compatibility)

Main: **CM0002E**
Scale Driver: J0994 (J0835)
OS:
 12.1 inch J1100-4
 10.1 inch J1100-2
BOOT: J1072C
FPGA App.: J1101
Scale: J0776L or later
Printer App: B0809B or later

NOTES:

- a) After downloading the Main program, download the Printer Sub App and FPGA Sub App programs one at a time as needed.
- b) After changing the color printer connection method or IP address the Uni-10 must be rebooted to activate the change [Setup menu → Machine No. → Outside Printer]

CM0001x MAIN FIRMWARE RELEASE NOTES

Ishida Uni-10 Series – with Support for the Epson ColorWorks Printer



Caution

Memory initialization **is required** when upgrading to this firmware version. Use SLP-5 Maintenance Utility and SLP-5 to backup the scale before upgrading from firmware **CM0001D** or an earlier version. Due to significant changes in the memory structure, after firmware installation a standard memory clear will be necessary: **Master Data Clear** (Adjust menu → Memory Clear) & **System Data Init.** (Setup menu → File Save/Load → Scale Init. tab). [8.6.1921.6]

The following lists the main changes from the previous version (CM0001D).

1. Modified operation of the Auto Print Delay to also apply after the first label for weighed items.
2. Removed a duplicate listing of Use By Date Print in the Receive Control menu (Setup menu → Machine No. → PC Comm tab).
3. Modified Store and Cooking Time lists to select an item by double tapping to match other lists (Program menu).
4. Added date format options to the Custom Barcode (Setup menu). The format selection is made by setting the Start value to one of the options 1-8.

1: YYYYMMDD	2: MMDDYYYY	3: DDMMYYYY
4: YYMMDD	5: MMDDYY	6: DDMMYY
	7: MMDD	8: DDMM

Version CM0001D

Release Date: May 2024

Use with SLP-5 **2.62** or later (**required** for compatibility)

Main: **CM0002CD**
Scale Driver: J0994 (J0835)
OS:
 12.1 inch J1100-4
 10.1 inch J1100-2
BOOT: J1072C
FPGA App.: J1101
Scale: J0776L or later
Printer App: B0809B or later

NOTES:

- a) After downloading the Main program, download the Printer Sub App and FPGA Sub App programs one at a time as needed.
- b) After changing the color printer connection method or IP address the Uni-10 must be rebooted to activate the change [Setup menu → Machine No. → Outside Printer]



Caution

Memory initialization **is required** when upgrading to this firmware version. Use SLP-5 Maintenance Utility and SLP-5 to backup the scale before upgrading from firmware **CM0001C12** or an earlier version. Due to significant changes in the memory structure, after firmware installation a standard memory clear will be necessary: **Master Data Clear** (Adjust menu → Memory Clear) & **System Data Init.** (Setup menu → File Save/Load → Scale Init. tab). [8.6.1921.6]

The following lists the main changes from the previous version (CM0001C12).

1. Fixed a bug where the weight and tare values were not shown on the operation screen.

CM0001x MAIN FIRMWARE RELEASE NOTES

Ishida Uni-10 Series – with Support for the Epson ColorWorks Printer

Version CM0001C12

Release Date: April 2024

Use with SLP-5 **2.62** or later (required for compatibility)

Main: **CM0002C12**
Scale Driver: J0994 (J0835)
OS:
 12.1 inch J1100-4
 10.1 inch J1100-2
BOOT: J1072C
FPGA App.: J1101
Scale: J0776L or later
Printer App: B0809B or later

NOTES:

- a) After downloading the Main program, download the Printer Sub App and FPGA Sub App programs one at a time as needed.
- b) After changing the color printer connection method or IP address the Uni-10 must be rebooted to activate the change [Setup menu → Machine No. → Outside Printer]



Caution

Memory initialization is required when upgrading to this firmware version. Use SLP-5 Maintenance Utility and SLP-5 to backup the scale before upgrading from firmware **CM001C10** or an earlier version. Due to significant changes in the memory structure, after firmware installation a standard memory clear will be necessary: **Master Data Clear** (Adjust menu → Memory Clear) & **System Data Init.** (Setup menu → File Save/Load → Scale Init. tab). [8.6.1921.6]

The following lists the main changes from the previous version (CM0001C10).

1. Modified the operation of the ADD function.
 - a. Allow accumulation format #98 to expand when using continuous label.
 - b. Display an error with instructions when the maximum 20 items have been accumulated.
 - c. Automatically clear the accumulation and return to the main screen after the label has been printed.
 - d. Change the title at the top of the center column to "QTY/WGT".
 - e. Print "lb" after the weight for weighed items on the label.
 - f. When OK is pressed at message 11045-0002 "MAXIMUM ITEMS HAVE BEEN ACCUMULATED", go to the PLU Memory screen listing the accumulated items.
 - g. Fix problem where odd characters are displayed following the Tare and Weight titles on the main screen after printing the accumulated label.
 - h. Fix a problem where the scale locked up when printing the accumulated label if a PLU has only one line of description.
 - i. Add the option to print a fixed barcode or the barcode of the first accumulated PLU.
Setup menu → Operation Settings → Print tab → Accum. Barcode Print.

Notes:

- The fixed barcode is set at Setup menu → Receipt Setting → Barcode tab → Receipt Code.
- The label header title is set at Setup menu → Receipt Setting → Title tab → Header Text

CM0001x MAIN FIRMWARE RELEASE NOTES

Ishida Uni-10 Series – with Support for the Epson ColorWorks Printer

Version CM0001C10

Release Date: April 2024

Use with SLP-5 **2.62** or later (**required** for compatibility)

Main: **CM0002C10**
Scale Driver: J0994 (J0835)
OS:
 12.1 inch J1100-4
 10.1 inch J1100-2
BOOT: J1072C
FPGA App.: J1101
Scale: J0776L or later
Printer App: B0809B or later

NOTES:

- a) After downloading the Main program, download the Printer Sub App and FPGA Sub App programs one at a time as needed.
- b) After changing the color printer connection method or IP address the Uni-10 must be rebooted to activate the change [Setup menu → Machine No. → Outside Printer]



Caution

Memory initialization is required when upgrading to this firmware version. Use SLP-5 Maintenance Utility and SLP-5 to backup the scale before upgrading from firmware **CM001C6** or an earlier version. Due to significant changes in the memory structure, after firmware installation a standard memory clear will be necessary: **Master Data Clear** (Adjust menu → Memory Clear) & **System Data Init.** (Setup menu → File Save/Load → Scale Init. tab). [8.6.1921.6]

The following lists the main changes from the previous version (CM0001C6).

1. Modified the operation of the ADD function.
 - a. Fixed a bug where the scale locked up when the Return Arrow was pressed to go back to the main screen after printing the accumulated label.
 - b. Changed the title of the message 11045-0002 to "MAXIMUM ITEMS HAVE BEEN ACCUMULATED".
 - c. Changed the "RECEIPT PRINT" button to "PRINT ACCUM." and changed the button color to green to highlight it
 - d. Remove the "PRINT" key from the accumulation screen.
 - e. Changed to display the Quantity as "X PC" instead of "X EA".
 - f. Changed the prices to print with right justification on accumulation format #98.
 - g. Changed unit for fixed price items from "QTY" to "PC".

Version CM0001C6

Release Date: March 2024

Use with SLP-5 **2.62** or later (**required** for compatibility)

Main: **CM0002C6**
Scale Driver: J0994 (J0835)
OS:
 12.1 inch J1100-4
 10.1 inch J1100-2

CM0001x MAIN FIRMWARE RELEASE NOTES

Ishida Uni-10 Series – with Support for the Epson ColorWorks Printer

BOOT: J1072C
FPGA App.: J1101
Scale: J0776L or later
Printer App: B0809B or later

NOTES:

- a) After downloading the Main program, download the Printer Sub App and FPGA Sub App programs one at a time as needed.
- b) After changing the color printer connection method or IP address the Uni-10 must be rebooted to activate the change [Setup menu → Machine No. → Outside Printer]



Caution

Memory initialization **is required** when upgrading to this firmware version. Use SLP-5 Maintenance Utility and SLP-5 to backup the scale before upgrading from firmware **CM001C5** or an earlier version. Due to significant changes in the memory structure, after firmware installation a standard memory clear will be necessary: **Master Data Clear** (Adjust menu → Memory Clear) & **System Data Init.** (Setup menu → File Save/Load → Scale Init. tab). [8.6.1921.6]

The following lists the main changes from the previous version (CM0001C5).

1. Added the ADD function to accumulate PLUs for "build a sandwich" or similar operations.
 - a. Added preset function key 524: ADD.
 - b. Weighed and Fixed Price items may be accumulated.
 - c. The Unit Price and Quantity may be changed on the accumulated (PLU Memory) screen.
 - d. The ADD key is a split key. The lower half displays the status:
 - NONE: no PLUs have been accumulated (white background)
 - WAITING: one or more PLUs have been accumulated (green background)
 - There is no need to split the key on the Function key page. The button is just pressed to add items to the accumulation.
 - Press the ADD key from the main screen to display the list of accumulated items.
 - e. Up to 20 items may be accumulated.
 - f. The accumulated items are printed using label format #98.
 - g. The barcode is set at Setup menu → Receipt Setting → Barcode tab → Receipt Code.
 - h. After printing the accumulated label, a prompt is displayed to clear the items from memory.

Version CM0001C5

Release Date: December 2023

Use with SLP-5 **2.62** or later (**required** for compatibility)

Main: **CM0002C5**
Scale Driver: J0994 (J0835)
OS:
 12.1 inch J1100-4
 10.1 inch J1100-2
BOOT: J1072C
FPGA App.: J1101
Scale: J0776L or later
Printer App: B0809B or later

CM0001x MAIN FIRMWARE RELEASE NOTES

Ishida Uni-10 Series – with Support for the Epson ColorWorks Printer

NOTES:

- After downloading the Main program, download the Printer Sub App and FPGA Sub App programs one at a time as needed.
- After changing the color printer connection method or IP address the Uni-10 must be rebooted to activate the change [Setup menu → Machine No. → Outside Printer]



Caution

Memory initialization is required when upgrading to this firmware version. Use SLP-5 Maintenance Utility and SLP-5 to backup the scale before upgrading from firmware **CM0001C** or an earlier version. Due to significant changes in the memory structure, after firmware installation a standard memory clear will be necessary: **Master Data Clear** (Adjust menu → Memory Clear) & **System Data Init.** (Setup menu → File Save/Load → Scale Init. tab). [8.6.1921.6]

The following lists the main changes from the previous version (CM0001C).

- Fixed a bug where the price could not be changed on the PLU List screen: Program menu → PLU.
- Added a "Setup Password" **951753** to enable Setup menu items for an IT department or advanced end user. This avoids the need to provide the service password. Additional steps are:
 - Machine No. – all settings, including PLU Receive filter
 - Cassette
 - Label Format
 - Barcode
 - Operation Settings
 - Error Process
- Added support for the preset key Style "NO" to communication with SLP-5. This style support images only with no background key outline. Current descriptions at the Uni-10 in SLP-5 as of version 2.62.

Uni-10	SLP-5
ANGLE	Thick Box
ROUND	Thick Corner Round
NO	Flat Box
- Fixed a bug where sending preset keys to the Uni-10 could cause an "out of range" error in SLP-5.

Version CM0001C

Release Date: October 2023

Use with SLP-5 **2.62** or later (required for compatibility)

Main: **CM0002C**

Scale Driver: J0994 (J0835)

OS:

12.1 inch J1100-4

10.1 inch J1100-2

BOOT: J1072C

FPGA App.: J1101

Scale: J0776L or later

Printer App: B0809B or later

CM0001x MAIN FIRMWARE RELEASE NOTES

Ishida Uni-10 Series – with Support for the Epson ColorWorks Printer

NOTES:

- After downloading the Main program, download the Printer Sub App and FPGA Sub App programs one at a time as needed.
- After changing the color printer connection method or IP address the Uni-10 must be rebooted to activate the change [Setup menu → Machine No. → Outside Printer]



Caution

Memory initialization is required when upgrading to this firmware version. Use SLP-5 Maintenance Utility and SLP-5 to backup the scale before upgrading from firmware **CM0001B** or an earlier version. Due to significant changes in the memory structure, after firmware installation a standard memory clear will be necessary: **Master Data Clear** (Adjust menu → Memory Clear) & **System Data Init.** (Setup menu → File Save/Load → Scale Init. tab). [8.6.1921.6]

The following lists the main changes from the previous version (CM0001B).

- Fixed a bug where the "\$" did not print correctly for font sizes 14x10, 24x18, 34x16, and 56x24.
- Fixed a bug where the markdown price calculation was incorrect when the number of pieces was changed in operation mode.
- Fixed a bug where the markdown price was not displayed correctly on the customer side display.
- Fixed a bug where the markdown price was not displayed on the customer display when the PLU was in a Campaign.
- Fixed a bug where a custom barcode was not correctly linked to a QR Code.
- Fixed the "/FOR" field to print correctly.
- Fixed the label preview to display correctly.
- Modified the Calculated Unit Price (Print ID 1A8) to print only when the PLU Sales Mode is "2:Wgt w/ Fixed Price".
- Added a slash symbol "/" to indicate the line break when displaying PLU lists where the PLUs have multiple lines in the description.

Version CM0001B

Release Date: July 2023

Use with SLP-5 **2.62** or later (required for compatibility)

Related Programs

Main: **CM0002B**
Scale Driver: J0994 (J0835)
OS:
 12.1 inch J1100-4
 10.1 inch J1100-2
BOOT: J1072C
FPGA App.: J1101
Scale: J0776L or later
Printer App: B0809B or later

NOTES:

- After downloading the Main program, download the Printer Sub App and FPGA Sub App programs one at a time as needed.
- After changing the color printer connection method or IP address the Uni-10 must be rebooted to activate the change [Setup menu → Machine No. → Outside Printer]

CM0001x MAIN FIRMWARE RELEASE NOTES

Ishida Uni-10 Series – with Support for the Epson ColorWorks Printer



Caution

Memory initialization is required when upgrading to this firmware version. Use SLP-5 Maintenance Utility and SLP-5 to backup the scale before upgrading from firmware **CM0001A** or an earlier version. Due to significant changes in the memory structure, after firmware installation a standard memory clear will be necessary: **Master Data Clear** (Adjust menu → Memory Clear) & **System Data Init.** (Setup menu → File Save/Load → Scale Init. tab). [8.6.1921.6]

The following lists the main changes from the previous version (CM0001A).

1. Changed the function key numbers to avoid duplication with other models. Numbers 521 to 540 are reserved for the Uni-10.
 - 521: MES SEARCH
 - 522: PLU(+No.)
 - 523: BACKGROUND

Version CM0001A

Release Date: May 2023

Use with SLP-5 **2.62** or later (**required** for compatibility)

Related Programs

Main: **CM0002A**
Scale Driver: J0994 (J0835)
OS:
 12.1 inch J1100-4
 10.1 inch J1100-2
BOOT: J1072C
FPGA App.: J1101
Scale: J0776L or later
Printer App: B0809B or later

NOTES:

- a) After downloading the Main program, download the Printer Sub App and FPGA Sub App programs one at a time as needed.
- b) After changing the color printer connection method or IP address the Uni-10 must be rebooted to activate the change [Setup menu → Machine No. → Outside Printer]



Caution

Memory initialization is required when upgrading to this firmware version. Use SLP-5 Maintenance Utility and SLP-5 to backup the scale before upgrading from firmware **CM0001** or an earlier version. Due to significant changes in the memory structure, after firmware installation a standard memory clear will be necessary: **Master Data Clear** (Adjust menu → Memory Clear) & **System Data Init.** (Setup menu → File Save/Load → Scale Init. tab). [8.6.1921.6]

The following lists the main changes from the previous version (CM0001).

1. Fixed the size of the ISHIDA logo to appear on the customer side Display.
2. Fixed an issue where the Ad Message did not display the entire video.
3. Modified the Ad Message to play a silent video.
4. Modified to allow a PLU set as sale mode 3: Case Weight (Fix UPR) sent to the scale to include a fixed weight up to 99.999 lb.

CM0001x MAIN FIRMWARE RELEASE NOTES

Ishida Uni-10 Series – with Support for the Epson ColorWorks Printer

5. Added "Bakery (XL)" as an option for service support when the scale is not functioning. (Adjust menu → Machine Type).
6. Fixed a bug where PLU key type 468: PLU(+No.) could not be edited using the 447: Preset Edit function key.
7. Fixed the Time Zone to sound an error when the key is pressed and the service password has not been entered in the main menu. (Adjust menu → Date Time).
8. Fixed the Logo Image to display the description and icon correctly. (Program menu).
9. Fixed a bug where pressing the PLU name area after calling PLU did not display a label preview.
10. Fixed a bug causing abnormal behavior when printing a GTIN barcode due to the lack of buffer memory allocated for the data.
11. Added an "Update Thumbnail" setting to the File Save/Load menu → Detail. (Setup menu).
12. Fixed a bug where the scale would lockup when sending or receiving data to a USB. (Setup menu → File Save/Load).
13. Enhanced the search speed of function key 467: Ingredient Search.
14. Fixed a bug where the search results from a large amount of ingredients did not show all pages when using function key 467: Ingredient Search.

Version CM0001

Release Date: February 2023

Use with SLP-5 **2.62** or later (required for compatibility)

Related Programs

Main: CM0002

Scale Driver: J0994 (J0835)

OS:

12.1 inch J1100-4

10.1 inch J1100-2

BOOT: J1072C

FPGA App.: J1101

Scale: J0776L or later

Printer App: **B0809B** or later

NOTES:

- a) After downloading the Main program, download the Printer Sub App and FPGA Sub App programs one at a time as needed.
- b) After changing the color printer connection method or IP address the Uni-10 must be rebooted to activate the change [Setup menu → Machine No. → Outside Printer]



Caution

Memory initialization is required when upgrading to this firmware version. Use SLP-5 Maintenance Utility and SLP-5 to backup the scale before upgrading the firmware. Due to significant changes in the memory structure, after firmware installation a standard memory clear will be necessary: **Master Data Clear** (Adjust menu → Memory Clear) & **System Data Init.** (Setup menu → File Save/Load → Scale Init. tab). [8.6.1921.6]

The following lists the main changes from the previous version (Uni-9: C2417K).

1. CM0001 is the initial release of Uni-10 firmware.
2. Fixed a bug where Display and Logo images were not updated when sent to the scale.

CM0001x MAIN FIRMWARE RELEASE NOTES

Ishida Uni-10 Series – with Support for the Epson ColorWorks Printer

- a. When the Department function is disabled, the leading 4-digit number in the image file is now forced to be "0001". Example:
0000IMAGExxx.bmp → 0001IMAGExxx.bmp
0002IMAGExxx.bmp → 0001IMAGExxx.bmp
 - b. When the Department function is enabled, the leading 4-digit number in the image file is not changed.
 - c. The Department No. (=Network No.)
3. Added the NEXT key to scroll through search results when using function key 467:
Ingredient Search
4. Updated the Printer Sub App to B0809B to support Head Check Noise detection and fix a driver issue related to the UART.